

CCS Radio Configuration

CCS has standardized on FRS/GMRS radios. This type of radio is commonly used in many other LSC's. To insure that radios work together, we have selected Midland radios as the standard.

Midland Radio Configuration

New radios or sets should be configured as follows. When radio is setup, use the Lock function (hold down CALL button for 4 seconds) to protect the settings.

Standard

Setting	Value	Comment
Channel	7	
Privacy Type	Ct	
Privacy Code/Channel	7	
Power Level (Pr)	H	
Voice Activation (VOX)	oF	
Roger Beep (Rb)	oF	
Silent Operation (bP)	oF	

Alternate Configurations

Use an alternate configuration if there is radio interference at the meet location. Options are listed in order. Radios should be reconfigured by the end of the stroke briefing. (mid-meet may be necessary, should be coordinated and managed by the meet referee if required)

- 1) Option 2: Channel=5 Privacy Code=5
- 2) Option 3: Channel=1 Privacy Code=1
- 3) Option 4: Channel=3 Privacy Code=Off

Note: Channel and Privacy Code values are standard across Midland (CCS radio brand), Cobra, Motorola, Uniden, Backcountry Access, and Rocky Talkie radios. (useful if you have an out of LSC official who would like to use their own radio/headset)